


LIMON



总部：浙江省宁波市高新区清逸路215弄智造港D8、D9幢

华东：江苏省苏州市姑苏区平江万达广场写字楼B座2704

华南：深圳市宝安区新桥街道沙企社区中心路18号高盛大厦B808

Tel/电话：0086-0574-87515352

Head Office: Building D8-D9, Zhizaogang, Lane 215, Qingyi Road, High-tech
Zone, Ningbo city, Zhejiang, China

East China: Room 2704, Building Plaza, Pingjiang, Gusu District, Suzhou City
Jiangsu province

South China: B808 Goldman Sachs Building, No. 18 Zhongxin Road, Shaqi
Community, Xinqiao Street, Bao'an District, Shenzhen



中空旋转平台样册

Hollow Rotary Platform catalog

CAT F.2501




目 录

Contents


1-2	用语解说/应用案例 <i>Glossary Of Technical Terms/Application Examples</i>	
3-4	产品特征 <i>Features</i>	
5-9	DYH60	
10-17	DYH85	

目 录

Contents

18-23	DYH130	
24-28	DYH200	
29-32	DYH280	
33-36	马达安装说明 <i>Instructions of Motor Mounting</i>	


用语解说 Glossary Of Technical Terms



重复定位精度 Repeated positioning accuracy

以启动基准点设定为“0”点，做任何不同角度之往复运动，其每次回到启动点的精度误差值为“重复定位精度”所标示之数值。


Set the starting reference point as "0" point, which make reciprocating motion at any different angle, and the precision error value of each moving point is the "Repeated positioning accuracy", as marked.



相对精度 Relative accuracy

每次的启动点，均视为“0”点，由此点转动至下一个停止点的角度误差值为“相对精度”标示，下次再启动旋转所设定的角度时，以目前的停止点，视为新的“0”点。

Each starting point is regarded as "0" point, the angular error from this point to the next stop point is the marked "Relative accuracy". When the next time the rotation is started, the current stop point will be regarded as the new "0" point.



绝对精度 Absolute accuracy

以同一个启动点的设定：经任意角度旋转的单向定位精度皆处于“绝对精度”的范围内。

The setting of the same starting point: the single positioning accuracy rotated by any angle is within the range of "Absolute accuracy".

注：图表中的数据为范围数字，实际值请参阅“规格表”

Note: the data in the chart are sample data, please refer to the specification table for actual values.

应用案例 Application Examples

高性能、高刚性的用途

High performance & stiffness application

负载惯性产生变化的用途

Applications subject to changing load inertia




施以惯量载重的用途

Applications where a moment load is applied




光学用途

Optical applications using the hollow hole




高精度定位用途

High accuracy positioning applications



利用中空孔的高精度定位用途

High accuracy positioning applications using the hollow hole



安装方向自由设计

Flexible design of assembling direction

DY旋转平台除水平安装外，还可以垂直安装或倒挂安装，装置设计的范围较广。

DY rotary platform can be assembled in vertical direction or upside down direction as well as the parallel direction.


使用时注意事项：

中空旋转式传动装置偶尔会有少量润滑油渗出。如润滑油渗出导致周围环境污染，请在定期检查时进行确认或安装接油盘等装置。

Note:

Hollow rotary drive system will occur the exudation of few lubrication oil.

If the oil result in the environmental pollution, please check regularly or assemble the oil-receiving tray



产品特征 Features

■ 一体型产品 Integrated Products

DY系列为组合中空旋转平台与伺服马达的产品。平台内部为减速比构造，可实现高输出驱动。
DY series are combined with hollow rotary actuators platform and servo motor. Inside are reduction ratio device which can achieve high output drive.

■ 短时间定位 Short Positioning Time


可在短时间内实现惯性负载的定位
It can realize inertia load positioning in a short time.

■ 无齿隙的高精度定位 High Accuracy Positioning With Zero Backlash

无齿隙，螺旋斜齿，研磨机齿轮：齿轮模数大，实现高扭矩反复定位精度 $\pm 15\text{arcsec}$ ($\pm 0.04^\circ$)
*精度是在一定负载、一定温度（常温）下的数值。
Zero backlash, spiral gear, grinding machine gear: high tooth module to achieve high torque. Repetitive Accuracy: $\pm 15\text{arcsec}$ ($\pm 0.04^\circ$)
Note: The repetitive positioning accuracy is measured at a constant temperature (normal temperature) under a constant load.

■ 减少设计时间，缩短交期 Reduce Design Time And Shorten The Delivery



输出平台可直接安装设备的工作台或机械手臂，与使用皮带、皮带轮等机械零件时比较，可以减少机构设计。零件调配、皮带张力调整等时间及成本节省设备设计时间，有助于缩短交期。
Equipment tables and arms can be installed directly on the output table. This saves you the hassle and cost of designing an installation mechanism, arranging necessary parts, adjusting the belt tension, etc. when mechanical parts such as belt and pulley are used for installation.



■ 大口径中空输出平台节省配线与配管 Large-Diameter, Hollow Output Table Makes Simple Wiring and Piping Possible

大口径的中空孔（贯穿）可利用在环境复杂的配线管上，可简化设备设计。
The large diameter hollow hole (through-hole) helps reduce the complexity of wiring and piping, thus simplifying your equipment design.


	安装尺寸mm Frame Size	中空径 Diameter of Hollow Section
DYH60	60	$\phi 28$
DYH85	85	$\phi 33$
DYH130	130	$\phi 62$
DYH200	200	$\phi 100$
DYH280	280	$\phi 150$



产品特征 Features

■ 高输出 高刚性 High Power and Rigidity

Standard Type的输出平台轴承使用径、轴向轴承，实现了高载重、高刚性。
<输出> 最大容许惯量 $200\text{N}\cdot\text{m}$
<刚性> 最大容许轴心方向载重 $500\text{N}\cdot\text{m}$
型号越大容许惯量越大，相对于负载惯量的变形位移量就越小。
The standard type-hollow output table is integrated with a high rigidity cross roller bearing to achieve high load and high rigidity.
<output> max permissible inertia $200\text{N}\cdot\text{m}$
<rigidity> max permissible load in axis direction $500\text{N}\cdot\text{m}$.
Larger size with bigger permissible inertia, and smaller deformation displacement relative to load inertia.




■ 高刚性 High Rigidity

在距离平台中央部160mm的位置有10kg的工作物时，惯量为 $15.7\text{N}\cdot\text{m}$ 。
When there is 10kg object working in the place which is distant 160mm from center plate, the inertia is $15.7\text{N}\cdot\text{m}$.


$$10\text{kg} \times \text{gm/s}^2 \times 0.16\text{m} = 15.7\text{N}\cdot\text{m}.$$

DYH200的容许惯量为 $200\text{N}\cdot\text{m}$ ，在容许值以内。
The DYH200's permissible inertia is $200\text{N}\cdot\text{m}$ within the permissible value.



■ 高刚性 High Rigidity

品名: DYH200 电源输入: AC220V
Name: DY200-10 Input Power: AC200V
搬运重量: 91kg (工作物6个+平台)
: 工作物10kg/个×6个
: 平台31kg
(直径500mm、厚度200mm、铁质)
Weight: 91kg (working objects 6pcs+table)
working objects 10kg/pcs*6pcs
table 31kg
(diameter 500mm, thickness 200mm, Iron Material)



■ 拥有【原点检知器套件】的选购配件 Home Sensor Suite Available for Optional Accessories


由于原点设定所需的零件齐全，因此可节省安装检知器的设计、制造、零件调配时间。
As the complete parts of home position setup, the time regarding design, manufacturing, parts allocation of assembling sensor can be saved.

■ 搭配方便 Easy Match


可任意搭配任何品牌的伺服马达或步进马达。
It can be matched with any brand of servo motor or stepper motor.

型号订购码 Code

DYH60	F	-	5	-	M10	-	RD3
本体型号 Item No.	马达连接方式 Lead Screw Specifications		减速比 Reduction ratio		马达类型 Motor type		提供伺服电机及驱动 Provide servo motors and drives
	F:标准型 F: Standard type		5		M10:三菱伺服100W Φ8, PCD46, M4 M10: Mitsubishi Servo100W Φ8, PCD46, M4		缺货: 不提供 Default: Not provided
	FP:行星型 FP: Planetary type		10		P10:松下伺服100W Φ8, PCD45, M3 P10: Panasonic Servo 100W Φ8, PCD45, M3		
	FR:直角型 FR: right-angled type		15		T1:42步进电机 Φ5, 31, M3 T1: 42 Stepper motor Φ5, 31, M3		
			20				
			25				
			50				




直角转向马达连接方式 Motor connection direction




技术参数 Technical Parameters

产品型号 Model Type	DYH60F	DYH60FP	DYH60FR
减速比 Reduction Ratio	5	15/20/25/50	10/15/25
容许扭矩(N-m) Permissible Torque (N-m)		5.2	
容许惯性力矩(N-m) Permissible Inertia Moment Load(N.M)		5	
容许轴向负载(N) Permissible Axial Load (N)		250	
定位精度(arc-min) Positioning Accuracy(arc-min)		≤3	
转台平面度(mm) Rotary table flatness(mm)		≤0.01	
转台同心度(mm) Rotary table concentricity(mm)		≤0.01	
重复定位精度(arc-sec) Repeatability accuracy(arc-sec)	≤15		≤120
容许盘面转速(rpm) Permissible table rotation speed		200	
角度范围(°) Angle range(°)		360	
重量(kg) Weight(kg)	0.6	1	1.1
使用温度(°C) Operating temperature(°C)		-25~+90	
防护等级 Protection Grade		IP40	


定位检测精度 Module Dimension




DYH60F-5-M10




2D&3D文档下载请至
www.limonrobot.cn




DYH60F-5-P10




2D&3D文档下载请至
www.limonrobot.cn




DYH60F-5-T1




DYH60FP-15(20/25/50)-P10




DYH60FP-15(20/25/50)-M10




DYH60FR-10(15/25)-M10



DYH60FR-10(15/25)-P10




2D&3D文档下载请至
www.limonrobot.cn




型号订购码 Code

DYH85	F	-	5	-	M40	-	RD3
本体型号 Item No.	马达连接方式 Lead Screw Specifications		减速比 Reduction ratio		马达类型 Motor type		提供伺服电机及驱动 Provide servo motors and drives
	F:标准型 F: Standard type		5		M40:三菱伺服400W Φ14, PCD70, M5 M40: Mitsubishi Servo400W Φ14, PCD70, M5		缺省: 不提供马达 Default: Not provided
	FP:行星型 FP: Planetary type		10		P20:松下伺服200W Φ11, PCD70, M4 P20: Panasonic Servo200W Φ11, PCD70, M4		
	FR:直角型 FR: right-angled type		30		P40:松下伺服400W Φ14, PCD70, M4 P40: Panasonic Servo400W Φ14, PCD70, M4		
			40				
			50				
					T2:57步进电机 Φ8, 47.14, M4 T2: 57 Stepper motor Φ8, 47.14, M4		
					T2S:57步进电机 Φ6.35, 47.14, M4 T2S: 57 Stepper motor Φ6.35, 47.14, M4		




直角转向马达连接方式 Motor connection direction




技术参数 Technical Parameters

产品型号 ModelType	DYH85F		DYH85FP		DYH85FR
减速比 iReduction Ratio	5	10	30,40,50		30,40,50
容许扭矩(N·m)	20	16		16	
容许转矩(N·m)					
容许惯性力矩(N·m)			10		
容许轴向负载(N)			500		
定位精度(arc-min)			≤3		
转台平面度(mm)			≤0.01		
转台同心度(mm)			≤0.01		
重复定位精度(arc-sec)		≤15		≤120	
容许盘面转速(rpm)			200		
角度范围(°)			360		
重量(kg)	1.4		2.6		2.6
使用温度(°C)			-25~+90		
防护等级			IP40		



定位检测精度 Module Dimension




DYH85F-5-M40





DYH85F-5-P40



DYH85F-5-P20





DYH85F-5-T2/T2S




马达类型 Motor types	马达轴径 ϕD Motor shaft diameter
T2	$\phi 8$
T2S	$\phi 6.35$



DYH85F-10-M40




DYH85F-10-P40



DYH85F-10-P20




DYH85F-10-T2/T2S




马达类型 Motor types	马达轴径φD Motor shaft diameter
T2	φ8
T2S	φ6.35


DYH85FP-30(40)(50)-M40




DYH85FP-30(40)(50)-P40



DYH85FP-30(40)(50)-P20





DYH85FR-30(40)(50)-M40



DYH85 中空旋转平台
DYH85 Hollow Rotary Actuators

DYH130 中空旋转平台
DYH130 Hollow Rotary Actuators



DYH85FR-30(40)(50)-P20



型号订购码 Code

DYH130	F	-	10	-	M40	-	RD3
本体型号 Item No.	马达连接方式 Lead Screw Specifications		减速比 Reduction ratio		马达类型 Motor type		提供伺服电机及驱动 Provide servo motors and drives
	F: 标准型 F: Standard type		10		M40: 三菱伺服400W Φ14, PCD70, M5 M40: Mitsubishi Servo 400W Φ14, PCD70, M5		缺省: 不提供 Default: Not provided
	FP: 行星型 FP: Planetary type		18		P20: 松下伺服200W Φ11, PCD70, M4 P20: Panasonic Servo 200W Φ11, PCD70, M4		
	FR: 直角型 FR: right-angled type		30		P40: 松下伺服400W Φ14, PCD70, M4 P40: Panasonic Servo 400W Φ14, PCD70, M4		
			40		T2: 57步进电机 Φ8, 47.14, M4 T2: 57 Stepper motor Φ8, 47.14, M4		
			50		T2S: 57步进电机 Φ6.35, 47.14, M4 T2S: 57 Stepper motor Φ6.35, 47.14, M4		


直角转向马达连接方式 Motor connection direction




技术参数 Technical Parameters

产品型号 ModelType	DYH130F		DYH130FP	DYH130FR
减速比 iReduction Ratio	10	18	30,40,50	30,50
容许扭矩(N·m) Permissible Torque (N·m)	30	18		30
容许惯性力矩(N·m) Permissible inertia Moment Load(N·m)			50	
容许轴向负载(N) Permissible Axial Load (N)			2000	
定位精度(arc-min) Positioning Accuracy(arc-min)			≤3	
转台平面度(mm) Rotary table flatness(mm)			≤0.01	
转台同心度(mm) Rotary table concentricity(mm)			≤0.01	
重复定位精度(arc-sec) Repeatability accuracy(arc-sec)		≤15		≤120
容许盘面转速(rpm) Permissible table rotation speed	200	150		200
角度范围(°) Angle range(°)		360		
重量(kg) Weight(kg)	2.5		3.8	3.8
使用温度(°C) Operating temperature(°C)		-25~+90		
防护等级 Protection Grade		IP40		


定位检测精度 Module Dimension




外径任意点定位精度
Positioning Accuracy of Arbitrary Point in Outer Diameter.
半径65mm
Radius 65mm
≤3min





反复定位精度
Repetitive Accuracy Radius
半径65mm
Radius 65mm
DYH130F: ≤15sec
DYH130FP/DYH130FR: ≤120sec





DYH85FR-30(40)(50)-P40





DYH130F-10(18)-M40





DYH130F-10(18)-P40



DYH130F-10(18)-P20




DYH130F-10(18)-T2/T2S




马达类型 Motor types	马达轴径φD Motor shaft diameter
T2	φ8
T2S	φ6.35


DYH130FP-30(40)(50)-M40




DYH130FP-30(40)(50)-P40




DYH130FP-30(40)(50)-P20




DYH130FR-30(50)-M40



DYH200F-10(18)-M75




DYH200F-10(18)-T3/T3S




马达类型 Motor types	马达轴径 ϕD Motor shaft diameter
T3	$\phi 14$
T3S	$\phi 12.7$


DYH200F-10(18)-P75




DYH200FP-30(40)(50)-M75




DYH200FP-30(40)(50)-P75



DYH200FR-30(50)-P75




DYH200FR-30(50)-M75




型号订购码 Code

DYH280 本体型号 Item No.	F 马达连接方式 Lead Screw Specifications F:标准型 FP:行星型 FR:直角型	-	10 减速比 Reduction ratio 10 18 30	-	M1KH 马达类型 Motor type M1KH:三菱伺服1000W Φ24, PCD145, M8 M1KH: Mitsubishi Servo1000W Φ24, PCD145, M8 PIKH:松下伺服1000W Φ22, PCD145, M8 PIKH: Panasonic Servo 1000W Φ22, PCD145, M8	-	RD3 提供伺服电机及驱动 Provide servo motors and drives 缺省: 不提供 Default: Not provided
-----------------------------------	--	----------	---	----------	---	----------	--




直角转向马达连接方式 Motor connection direction







技术参数

产品型号 ModelType	DYH280F		DYH280FP	DYH280FR
减速比 iReduction Ratio	10	18	30	
容许扭矩(N·m)	87	65	87	
容许惯性力矩(N·m)	135	105	135	
容许轴向负载(N)	4840			
定位精度(arc-min)	≤3			
转台平面度(mm) Rotary table flatness(mm)	≤0.01			
转台同心度(mm) Rotary table concentricity(mm)	≤0.01			
重复定位精度(arc-sec)	≤15arc-sec		≤2arc-min	
容许盘面转速(rpm)	200	150	200	
角度范围(°) Angle range(°)	360			
重量(kg) Weight(kg)	25	46	34	
使用温度(°C) Operating temperature(°C)	-25~+90			
防护等级 Protection Grade	IP40			

定位检测精度







DYH280F-10/18-M1KH




2D&3D文档下载请至
www.limonrobot.cn

DYH280F-10/18-P1KH




2D&3D文档下载请至
www.limonrobot.cn


DYH280FP-30-M1KH




DYH280FR-30-M1KH



DYH280FP-30-P1KH



DYH280FR-30-P1KH



惯量计算范例 Inertia Calculation Example

如图(1)所示。

假设 $a=400\text{mm}$, $b=600\text{mm}$, 质量 m 为 40kg

今令其每秒转 90°

①先求转动惯量:

$$I = 1/12 m(a^2 + b^2) = 1/12 * 40 * (0.4^2 + 0.6^2) = 1.73\text{kg}\cdot\text{m}^2$$

②求转动加速力矩:

$$M = I * \alpha \text{ 其中 } \alpha = \omega / T$$

$$\omega = 2\pi N \text{ (每秒转动 } 360^\circ = 2\pi, 180^\circ = \pi, 90^\circ = 1/2\pi)$$

$$\text{(revolve } 360^\circ \text{ per second} = 2\pi, 180^\circ = \pi, 90^\circ = 1/2\pi)$$

因要求每秒 90° , 角加速度设定其 0.5 秒

$$\text{得 } \alpha = 1/2\pi / 0.5 = 3.14$$

$$\text{故 } M = 1.73 * 3.14 = 5.4\text{N}\cdot\text{m}$$

① Calculate the rotary inertia:

$$I = 1/12 m(a^2 + b^2) = 1/12 * 40 * (0.4^2 + 0.6^2) = 1.73\text{kg}\cdot\text{m}^2$$

② Calculate the rotary accelerating moment:

$$M = I * \alpha \text{ which } \alpha = \omega / T$$

$$\omega = 2\pi N \text{ (revolve } 360^\circ \text{ per second} = 2\pi, 180^\circ = \pi, 90^\circ = 1/2\pi)$$

As it requires 90° per second, assuming the angular acceleration is 0.5 second.

$$\text{So } \alpha = 1/2\pi / 0.5 = 3.14 \text{ And } M = 1.73 * 3.14 = 5.4\text{N}\cdot\text{m}$$

如图(2)所示。

假设圆盘半径 $r=300\text{mm}$, 质量 m 为 40kg

今令其每秒转 180°

①先求转动惯量:

$$I = mr^2/2 = 40 * 0.3^2 / 2 = 1.8\text{kg}\cdot\text{m}^2$$

②求转动加速力矩:

$$M = I * \alpha \text{ 其中 } \alpha = \omega / T$$

$$\omega = 2\pi N \text{ (每秒转动 } 360^\circ = 2\pi, 180^\circ = \pi)$$

因要求每秒 180° , 角加速度设定其 0.5 秒

$$\text{得 } \alpha = \pi / 0.5 = 3.14 / 0.5 = 6.28$$

$$\text{故 } M = 1.8 * 6.28 = 11.3\text{N}\cdot\text{m}$$

As picture(2)

Assume Radius of the circular disk $r=300\text{mm}$, weight $m=40\text{kg}$,

And make it revolve 180° per second.

① Calculate the rotary inertia:

$$I = mr^2/2 = 40 * 0.3^2 / 2 = 1.8\text{kg}\cdot\text{m}^2$$

② Calculate the rotary accelerating moment:

$$M = I * \alpha \text{ which } \alpha = \omega / T$$

$$\omega = 2\pi N \text{ (revolve } 360^\circ \text{ per second} = 2\pi, 180^\circ = \pi, 90^\circ = 1/2\pi)$$

As it requires 180° per second, assuming the angular acceleration is

0.5 second.

$$\text{So } \alpha = \pi / 0.5 = 3.14 / 0.5 = 6.28 \text{ And } M = 1.8 * 6.28 = 11.3\text{N}\cdot\text{m}$$




图 (1) Picture(1)




图 (2) Picture(2)

如图(3)所示。

假设圆盘半径 $r=100\text{mm}$,

Z_0 到 Z_1 的 $d=300\text{mm}$, $a=1000\text{mm}$, $b=600\text{mm}$,

方形盘质量 m 为 50kg , 圆柱体质量为 10kg

今令其每秒转 90°

①先求转动惯量:

$$I_1 = 1/12 m(a^2 + b^2) = 5.67\text{kg}\cdot\text{m}^2$$

$$I_2 = mr^2/2 + md^2 = 1.4\text{kg}\cdot\text{m}^2$$

$$I = I_1 + I_2 = 5.67 + 1.4 = 7.07\text{kg}\cdot\text{m}^2$$

②求转动加速力矩:

$$M = I * \alpha \text{ 其中 } \alpha = \omega / T$$

$$\omega = 2\pi N \text{ (每秒转动 } 360^\circ = 2\pi, 180^\circ = \pi, 90^\circ = 1/2\pi)$$

因要求每秒 90° , 角加速度设定其 0.5 秒

$$\text{得 } \alpha = 1/2\pi / 0.5 = 3.14$$

$$\text{故 } M = 7.07 * 3.14 = 22.2\text{N}\cdot\text{m}$$

As picture(3)

Assume Radius of Cylinder $r=100\text{mm}$, $b=600\text{mm}$

Square disk mass is 50kg , Cylinder mass is 10kg ,

And make it revolve 90° per second.

① Calculate the rotary inertia:

$$I_1 = 1/12 m(a^2 + b^2) = 5.67\text{kg}\cdot\text{m}^2$$

$$I_2 = mr^2/2 + md^2 = 1.4\text{kg}\cdot\text{m}^2$$

$$I = I_1 + I_2 = 5.67 + 1.4 = 7.07\text{kg}\cdot\text{m}^2$$

② Calculate the rotary accelerating moment:

$$M = I * \alpha \text{ which } \alpha = \omega / T$$

$$\omega = 2\pi N \text{ (revolve } 360^\circ \text{ per second} = 2\pi, 180^\circ = \pi, 90^\circ = 1/2\pi)$$

As it requires 90° per second, assuming the angular acceleration is 0.5 second.

$$\text{So } \alpha = 1/2\pi / 0.5 = 3.14 \text{ And } M = 7.07 * 3.14 = 22.2\text{N}\cdot\text{m}$$

用语注释说明 Terminology Annotation and Explanation

*1容许转矩: 减速机构部的机械强度界限值。包括加速转矩、负载惯量, 皆须在此容许转矩范围内使用。

*2允许转速: 减速机构部的机械强度可允许的旋转平台之盘面转速。

*3定位精度: 选装平台盘面于 360° 以内所累计的定位角度误差总和。

*4重复精度: 旋转平台在任一点做正转方向定位, 再由逆转方向定位的相对角度误差。

*5旋转平台平行度: 旋转平台盘面运转时相对于底座安装面的平行度。

*6旋转平台同心度: 指无负载时旋转平台内径与外径的同心度误差值。

1. Permissible torque : mechanical strength threshold value in the reducing gear part, including the accelerating torque, load inertia, all should be within the permissible torque.

2. Permissible rotating speed : round plate rotating speed in the rotary table which is within the mechanical strength's permission in reducing gear part.

3. Positioning accuracy : accumulated positioning angle error summation within 360° in the rotary table.

4. Repetitive accuracy : the relative angle error regarding forward positioning in any point of rotary table compared with reverse positioning.

5. Parallelism of rotary table : Parallelism when the rotary table in round plate revolving relative to bottom base assembling surface.

6. Concentricity of rotary table : Concentricity error value of the rotary table 's outer diameter and internal diameter when without any load





图 (3) Picture (3)


马达安装说明 Instructions of Motor Mounting

1




确认马达和旋转平台的安装尺寸，并清除表面所有的异物
Confirm the assembling size of motor and rotary plate as well as remove all the foreign materials in the surface.

2




拆下马达法兰板的防尘塞，然后调整位置，直至能够看到紧固螺栓。查看(附件1)
Dismantle the dust plug in the motor flange plate, then adjust the place until the fastening bolt can be seen. (refer to attachment 1)

3




将马达与法兰板位置调整好，轻轻旋紧紧固螺栓，直至锁紧环不再空转。
Adjust the place of motor flange plate, then screw the fastening bolt gently until the binding ring no longer idle.

4




参照紧固扭力标准Ta，对角旋紧紧固螺栓。查看(附件2)
Confirm the assembling size of motor and rotary plate as well as remove all the foreign materials in the surface.

5



参照紧固扭力标准Tb,旋紧紧固螺栓。查看(附件2)
According to the tightening torque standard Tb ,screw the fastening bolt (refer to attachment 2)


6



安装防尘塞。
Assemble the dust plug

附件1 Attachment 1 如何安装马达 How to assemble the motor


A



锁紧环槽口 Binding Ring Notch
紧固螺栓 Fastening Bolt
锁紧环 Binding Ring
输入轴 Input Shaft
输入轴槽口 Input Shaft notch

附有机键的马达拔出机械键，调整锁紧环的位置使锁紧环槽口与输入轴槽口对齐，以便最大限度的紧固锁紧环的紧固螺栓。
Pull the motor out of mechanical key,then adjust the binding ring place to align the notch with the input shaft notch for screwing up the fastening bolt in the binding ring.

B



轴套槽口 Axle Sleeve Notch
轴套 Axle Sleeve

马达轴径与输入轴孔径不能匹配时，加入轴套，其安装方法与图A的安装方法一样，注意轴套槽口、输入轴槽口、锁紧环槽口要对齐。
If the motor shaft diameter can not match with the input shaft diameter, then add the axle sleeve (the assembling method is same with pic A).Please note that the notch of axle sleeve ,input shaft and binding ring are all in line.

附件2 Attachment 2 扳手螺栓紧固转矩 Fastening the torque by using the wrench bolt

扳手螺栓尺寸 Wrench Bolt Size	马达安装 Motor Mounting Ta-8.8T		锁紧环安装 Binding Ring Assembling Tb	
	N·m	N·m	kgf·cm	kgf·cm
M3	1.28	13	2.15	22
M4	2.9	30	4.95	50
M5	5.75	59	9.7	99
M6	9.9	101	16.5	168
M8	24	245	40	408
M10	48	489	81	826
M12	83	846	140	1428
M14	132	1346	220	2243
M16	200	2039	340	3467


中空旋转平台安装说明 Hollow Rotary Table Assembling Instructions

在中空旋转平台安装板上预留马达出口，以免马达与安装板干涉。
Reserve the place of motor outlet in the hollow rotary table assembling plate to avoid the mutual interference.

安装2个定位销孔将中空旋转平台定位，再对角旋紧紧固螺栓。
Assemble two dowel holes to fix the hollow rotary table, then screw up the binding bolt from corner.

注1 Note1 定位销孔尺寸 Dowel Size

平台规格 Table Specification	销孔直径 Pin Hole Diamete (mm)	销孔深度 Pin Hole Depth(mm)	销孔数量 Pin Hole Quantity
DYH60	φ3(H7)	5	2
DYH85	φ5(H7)	贯穿(through)	2
DYH130	φ5(H7)	贯穿(through)	2
DYH200	φ8(H7)	贯穿(through)	2
DYH280	φ8(H7)	贯穿(through)	2




中空旋转平台上安装负载 Assembling load in the hollow rotary table.

中空旋转平台2个负载的定位销孔，用于确认负载的位置。
将负载安装在中空旋转平台安装面，使用上面的6个螺纹孔完成对负载的紧定。
Assemble two loading dowel pins in the hollow rotary table to confirm the loading position.
Assemble the load in the hollow rotary table assembling plate , use the six taper holes above to finish load screwing.

注1 Note1 定位销孔尺寸 Dowel Size

平台规格 Table Specification	销孔直径 Pin Hole Diamete (mm)	销孔深度 Pin Hole Depth(mm)	销孔数量 Pin Hole Quantity
DYH60	φ3(H7)	6.35	2
DYH85	φ5(H7)	6.35	2
DYH130	φ5(H7)	6.35	2
DYH200	φ8(H7)	6.35	2
DYH280	φ8(H7)	6.35	2



定位销孔尺寸 Dowel Size

安装之前，应通读如下安装注意事项，并按照如下条件安装：
1.室内(不直接接触阳光的区域)
2.没有热辐射的区域
3.工作环境(温度:-25 ~ +90℃/湿度:低于85%)
4.原点感测器下方温度:0 ~ +40℃
5.不存在易燃易爆的酸性气体
6.可阻挡灰尘、油和溅水的地方
7.不遭受直接震动和过度撞击的地方
Before assembling,please read below attention matters and assemble according to the conditions:
1.Indoor (not exposed to the sunshine).
2.Without the heat radiation.
3.Working environment(temperature:0 ~ +50℃/humidity: lower than 85%)
4.The temperature below home sensor:0 ~ +40℃
5.Without inflammable and explosive acid gas
6.Place where cut off the dust, oil and splash

